

SVXLink

SVXLink sources

- <https://github.com/dl1hrc/svxlink/tree/tetra-contrib/> - Custom version that passes ISSIs through SVXReflector, it also **has our patches applied to SVXReflector and ReflectorLogic**.
- <https://github.com/sm0svx/svxlink/> - Original version

Note for owners of SVXLink nodes running TetraLogic

- Please use latest version of SVXLink software.
- Please use the same CALLSIGN in [ReflectorLogic] and [TetraLogic] to make our bridges pass talker ISSI correctly.

Note for owners of SVXReflector servers for TETRA

- Please use latest version of SVXReflector (at least 16082023) software.
- Reflector to Reflector links does not pass originating ISSI.

Administrating SVXLink bridges

Disclaimer about information bellow

- **DockStation** is only available on the same host as TetraPack Core, so the target of following information in this article is a server administrator.
- **DockLogic** is an external Logic module is supplied outside SVXLink.

Modules

- DockLogic.so - SVXLink Logic module that implements our own Dock IPC protocol, uses our own library CodecPack.so
- DockLogic.tcl - Supplementary script, required by SVXLink

Environment variables

```
CODECPACK=/<path>/CodecPack.so
```

svxlink.conf

```
[GLOBAL]
MODULE_PATH=/opt/SVXLink/lib/svxlink
CFG_DIR=/opt/SVXLink/etc/svxlink/svxlink.d
LOGICS=DockLogic,ReflectorLogic
LINKS=Link
TIMESTAMP_FORMAT="%c"

# Should be always 8 KHz!
CARD_SAMPLE_RATE=8000

[DockLogic]
TYPE=Dock
RX=Rx1
TX=Tx1
CALLSIGN=<Node call, should be completely the same as ReflectorLogic has>
EVENT_HANDLER=/opt/SVXLink/share/svxlink/events.tcl

# TetraPack Core IPC socket path
SOCKET=/tmp/Dock-<TetraPack Core ID>
```

GSSI at TetraPack Core

GSSI=<GSSI of talk group at TetraPack>

Default ISSI (used when ISSI is unknown)

ISSI=9999

MNI for Qso:info messages (4 digits for MCC and 5 digits for MNC)

MNI=090116383

[Rx1]

TYPE=Dock

[Tx1]

TYPE=Dock

Delay (in 60 ms frames) in bridged call start (SVXLink -> TetraPack), required for ISSI detection heuristics

DELAY=5

Gain before encoding to ACELP (0.1 .. 1.0, default is 0.5)

GAIN=0.5

[ReflectorLogic]

TYPE=Reflector

HOSTS=<SVXReflector's DNS/IP address>

CALLSIGN="<Node call>"

AUTH_KEY="<Key>"

UDP_HEARTBEAT_INTERVAL=5

DEFAULT_TG=<Bridged SVXReflector's TG>

MONITOR_TGS=<Bridged SVXReflector's TG>

EVENT_HANDLER=/opt/SVXLink/share/svxlink/events.tcl

MUTE_FIRST_TX_LOC=0

MUTE_FIRST_TX_REM=0

[Link]

CONNECT_LOGICS=DockLogic,ReflectorLogic

DEFAULT_ACTIVE=1

TIMEOUT=0

Revision #16

Created 14 August 2023 12:54:12 by R3ABM

Updated 9 November 2024 21:23:49 by R3ABM